

---

# ZigBee Plug-in for Inverters with SetApp Configuration

SE-ZBSLV-B-S1-RW



COMMUNICATION

## Wireless Smart Energy Solution

- ! ZigBee plug-in supports Smart Energy applications in Inverters with SetApp configuration
- ! Functions as Smart Energy network manager
- ! ZigBee Plug-in supports up to 10 Smart Energy devices
- ! Antenna external to inverter for wider range
- ! ZigBee Plug-in installed within the inverter enclosure for outdoor resilience

# ZigBee Plug-in for Inverters with SetApp Configuration

SE-ZBSLV-B-S1-RW

COMPATIBLE INVERTERS	SEXXXX-XXXXXBXX4 (INVERTERS WITH SETAPP CONFIGURATION)	UNIT
<b>SMART ENERGY NETWORK FUNCTIONALITY</b>		
Number of devices in a Smart Energy network	Up to 10	
Communications with Monitoring Platform	Single inverter installation - Ethernet / Wi-Fi <sup>(1)</sup> ; Multiple inverter installation - RS485 and Ethernet / Wi-Fi <sup>(1)</sup>	
<b>RF PERFORMANCE</b>		
Transmit Power	11.8	dBm
Receiver Sensitivity	-102	dBm
EIRP with Antenna	16.8	dBm
Maximum Emitted Power	≤20	dBm
Antenna Gain	5	dBi
Operating Frequency Range	2.4-2.5	GHz
Bandwidth	2	MHz
Modulation	O-QPSK with DSSS coding	
Outdoor (LOS) Range <sup>(2)</sup>	400 / 1300	m / ft
Indoor Range <sup>(2)</sup>	50 / 160	m / ft
<b>MECHANICAL SPECIFICATIONS</b>		
Antenna, Mounting Bracket and RF Cable	Included	
Dimensions (L x W)	78 x 32 / 3 x 1.3	mm / in
Protection Rating	IP65	
<b>CERTIFICATION</b>		
Safety	IEC60950, UL60950	
EMC Approvals	ETSI (Europe), C-Tick (Australia), Telec (Japan)	

(1) Wi-Fi connectivity requires an external antenna. For more information refer to: <https://www.solaredge.com/sites/default/files/se-wifi-zigbee-antenna-datasheet.pdf>  
 (2) Approximate values, may differ depending on specific installation conditions

