

## ENERGY METER FOXESS DTSU666 THREE-PHASE

Product code: AF.licznik.foxess.02



The FoxESS DTSU666 three-phase four-wire electronic energy meter, designed for DIN rail mounting, is intended for monitoring energy consumption and meeting measurement needs in power systems, communication industries, and construction. It represents a new generation of intelligent devices, combining communication and measurement functions. Its main purpose is to measure voltage, current, power, frequency, power factor, active, and reactive power in electrical circuits. Through RS485 communication, it enables data transmission to external devices. It features a standard DIN 35 mm rail mounting structure and modular design, making it easy to install. Its advantages, such as compact size and ease of installation, make it widely used for monitoring and evaluating energy consumption in various sectors such as industrial, mining, hotels, schools, and large public buildings.

### Product variants

Index	Price
<b>ENERGY METER FOXESS DTSU666 THREE-PHASE</b> AF.licznik.foxess.02	Product prices only visible after login. If you do not have an account, please register.

### Product description

The FoxESS DTSU666 three-phase four-wire electronic energy meter, designed for DIN rail mounting, is intended for monitoring energy consumption and meeting measurement needs in power systems, communication industries, and construction. It represents a new generation of intelligent devices, combining communication and measurement functions. Its main purpose is to measure voltage, current, power, frequency, power factor, active, and reactive power in electrical circuits. Through RS485 communication, it enables data transmission to external devices. It features a standard DIN 35 mm rail mounting structure and modular design, making it easy to install. Its advantages, such as

compact size and ease of installation, make it widely used for monitoring and evaluating energy consumption in various sectors such as industrial, mining, hotels, schools, and large public buildings. Advantages of the FoxESS DTSU666 three-phase energy meter: Large LCD display Bi-directional, single-phase meter, DIN rail mountable Small size and easy installation Technical parameters of the FoxESS DTSU666 three-phase energy meter: Series and type: FoxESS DTSU666 three-phase energy meter FOXESS Nominal voltage (Un): 3x220/380V; 3x57.7/100V Operating range: 0.7 Un ~ 1.2 Un Power consumption: ≤ 1W, 5VA Current: CT 1.5 (6)A; DC: 5(80)A Frequency: 50 / 60 Hz LCD display: 7 segments dimensions: 5.3 mm x 2.8 mm Communication: RS485; Modbus and DL/T protocol