

SUN-50K-SG01HP3-EU-BM4 / SUN-80K-SG02HP3-EU-EM6

SUN-100K-PCSL01HP3

**BOS-A** 

#### SUN-50K-SG01HP3-EU-BM4 / SUN-80K-SG02HP3-EU-EM6

## Practicality & Universal Compatibility

O Dual Independent battery circuit

O AC couple to retrofit existing solar system

I00% unbalanced output

### 🚯 Versatile & High-Performance

 TOU function,Six time periods for battery charging/discharging
 Diesel generator-ready,VSG application

#### (0) Reliability & Scalability

Max. 10 pcs parallel for on-grid and off-grid operation
 Seamless switching between on-grid and off-grid modes in less than 10ms

#### **BOS-A**

### 🔥 Intelligent Control

Over-discharge/charge/current and temp protection

10-Year Warranty
 Safest LFP battery&Intelligent BMS

## 🗓 Superior Output

Support up to 160A current output

- Survey Strategy Survey Strategy Survey Strategy Survey Sur
- $(\widehat{\underline{O}})$  Flexible Expansion
  - Support 7~21 packs in series
    Inverter 50~100kW, Battery 54~161kWh
  - Battery Protection
  - Auto-managed charge/discharge&Cell voltage balancing

#### SUN-50K-SG01HP3-EU-BM4

Model	SUN-50K-SG01HP3-EU-BM4
Battery Input Data	
Battery Type	Lithium-ion
Battery Voltage Range (V)	160-800
Max. Charging Current (A)	50+50
Max. Discharging Current (A)	50+50
Charging Strategy for Li-ion Battery	Self-adaption to BMS
Number of Battery Input	2
PV String Input Data	
Max. PV Access Power (W)	100000
Max. PV Input Power (W)	80000
Max. PV Input Voltage (V)	1000
Start-up Voltage (V)	180
MPPT Voltage Range (V)	150-850
Rated PV Input Voltage (V)	600
Max. Operating PV Input Current (A)	36+36+36
Max. Input Short-Circuit Current (A)	55+55+55
No. of MPP Trackers/	4/2+2+2
No. of Strings MPP Tracker	
AC Input/Output Data	
Rated AC Input/Output Active Power(W)	50000
Max. AC Input/Output Apparent Power(VA)	55000
Rated AC Input/Output Current (A)	75.8/72.5
Max. AC Input/Output Current (A)	83.4/79.8
Max. Continuous AC Passthrough (grid to load) (A)	200
Peak Power (off-grid) (W)	1.5 times of rated power, 10s
Power Factor Adjustment Range	0.8 leading to 0.8 lagging
Rated Input/Output Voltage/Range (V)	220/380V, 230/400V 0.85Un-1.1Un
Rated Input/Output Grid Frequency/Range(Hz)	50/45-55 60/55-65
Grid Connection Form	3L+N+PE
Total Current Harmonic Distortion THDi	<3% (of nominal power)
DC Injection Current	<0.5% In
Efficiency	
Max. Efficiency	97.60%
Euro Efficiency	97.0%
MPPT Efficiency	>99%
Equipment Protection	
Integrated	DC Polarity Reverse Connection Protection, AC Output Overcurrent Protection, Thermal Protection, AC Output Overvoltage Protection, AC Output Short Circuit Protection, DC Component Monitoring, Overvoltage Load Drop Protection, Ground Fault Current Monitoring, Arc Fault Circuit Interrupter (optional), Power Network Monitoring, Island Protection Monitoring, Earth Fault Detection, DC Input Switch, DC Terminal Insulation Impedance Monitoring, Residual Current (RCD) Detection, Surge protection level
Surge Protection Level	TYPE II(DC), TYPE II(AC)
Interface	
Communication Interface	RS485/RS232/CAN
Monitor Mode	GPRS/WIFI/Bluetooth/4G/LAN(optional)
General Data	
Operating Temperature Range(°C)	-40 to +60°C, >45°C Derating
Permissible Ambient Humidity	0-100%
Permissible Altitude	2000m
Noise(dB)	≤65
Ingress Protection (IP) Rating	IP 65
Inverter Topology	Non-Isolated
Over Voltage Category	OVC II(DC), OVC III(AC)
Cabinet Size (WxHxD mm)	527×894×294 (Excluding Connectors and Brackets)
Weight (kg)	80
Type of Cooling	Intelligent Air Cooling
Warranty	5 Years/10 Years
	the Warranty Period Depends the Final Installation Site of Inverter, More Info Please Refer to Warranty Policy IEC 61727, IEC 62116, CEI 0-21, EN 50549, NRS 097, RD 140, UNE 217002,
Grid Regulation	OVE-Richtlinie R25, G99, VDE-AR-N 4105
Safety / EMC Standard	IEC/EN 61000-6-1/2/3/4, IEC/EN 62109-1, IEC/EN 62109-2

01				
Model	SUN-60K-SG02HP3 -EU-EM6	SUN-70K-SG02HP3 -EU-EM6	SUN-75K-SG02HP3 -EU-EM6	SUN-80K-SG02HP3 -EU-EM6
Battery Input Data				
Battery Type		Lithiu	m-ion	
Battery Voltage Range (V)		160-	1000	
Max. Charging Current (A)		80	+80	
Max. Discharging Current (A)		80	+80	
Charging Strategy for Li-ion Battery		Self-adap	tion to BMS	
Number of Battery Input			2	
PV String Input Data				
Max. PV Access Power (W)	120000	140000	150000	160000
Max. PV Input Power (W)	96000	112000	120000	128000
Max. PV Input Voltage (V)	I	10	00	
Start-up Voltage (V)		18	80	
MPPT Voltage Range (V)		150-	-850	
Rated PV Input Voltage (V)		6	50	
Max. Operating PV Input Current (A)		36+36+36	+36+36+36	
Max. Input Short-Circuit Current (A)		54+54+54	+54+54+54	
No. of MPP Trackers/ No. of Strings MPP Tracker			2+2+2+2	
AC Input/Output Data				
Rated AC Input/Output Active Power(W)	60000	70000	75000	80000
Max. AC Input/Output Apparent Power(VA)	66000	77000	82500	88000
Rated AC Input/Output Current (A)	91/87	106.1/101.5	113.7/108.7	121.3/115.9
Max. AC Input/Output Current (A)	100/95.7	116.7/111.6	125/119.6	133.4/127.6
Max. Continuous AC Passthrough (grid to load) (A)	100/75./		0	133.4/127.0
Peak Power (off-grid) (W)			ated power, 10s	
Power Factor Adjustment Range			to 0.8 lagging	
			00 0	
Rated Input/Output Voltage/Range (V)		· · · · · · · · · · · · · · · · · · ·	00V 0.85Un-1.1Un	
Rated Input/Output Grid Frequency/Range(Hz)			60/55-65	
Grid Connection Form			N+PE	
Total Current Harmonic Distortion THDi			minal power)	
DC Injection Current		<0.5	5% In	
Efficiency				
Max. Efficiency			70%	
Euro Efficiency			10%	
MPPT Efficiency		>9	9%	
Equipment Protection				
Integrated	DC Polarity Reverse Connection Protection, AC Output Overcurrent Protection, Thermal Protection, AC Output Overvoltage Protection, AC Output Short Circuit Protection, DC Component Monitoring, Overvoltage Load Drop Protection, Ground Fault Current Monitoring, Arc Fault Circuit Interrupter (optional), Power Network Monitoring, Island Protection Monitoring, Earth Fault Detection, DC Input Switch, DC Terminal Insulation Impedance Monitoring, Residual Current (RCD) Detection, Surge protection level			
Surge Protection Level		TYPE II(DC)	, TYPE II(AC)	
Interface		DC 405 (D)	2070/041	
Communication Interface			S232/CAN	
Monitor Mode		GPRS/WIFI/Bluetoo	th/4G/LAN(optional)	
General Data		40.000		
Operating Temperature Range(°C)			>45 °C Derating	
Permissible Ambient Humidity	0-100%			
Permissible Altitude	3000m			
Noise (dB)			65	
Ingress Protection (IP) Rating		IP		
Inverter Topology	Non-Isolated			
Over Voltage Category		OVC II(DC),		
Cabinet Size (WxHxD mm)		606×927×314 (Excluding	g Connectors and Brackets	;)
Weight (kg)		10	5	
Type of Cooling		Intelligent	Air Cooling	
Warranty	the Warranty Period Dep		10 Years Site of Inverter, More Info P	lease Refer to Warranty Polic
Grid Regulation	IEC 61727		0549, NRS 097, RD 140, UI G99, VDE-AR-N 4105	NE 217002,
Safety / EMC Standard	IEC	VEN 61000-6-1/2/3/4 JEC	/EN 62109-1, IEC/EN 6210	9-2

PCS Model	SUN-100K-PCSL01HP3	SUN-125K-PCSL01HP3	
Battery Data			
Battery Type	Lithiur	m-ion	
Battery Voltage Range (V)	630-1	1000	
Max. Charging Current (A)	175	220	
Max. Discharging Current (A)	175	220	
Charging Strategy for Li-ion Battery	Self-adapti	on to BMS	
Number of Battery Input	1		
AC Input/Output Data			
Rated AC Input/Output Active Power (kW)	100	125	
Max. AC Input/Output Apparent Power (kVA)	110	125	
Rated AC Input/Output Current (A)	151.6/145	189.4/181.2	
Max. AC Input/Output Current (A)	166.7/159.5	189.4/181.2	
Rated Input/Output Voltage/Range(V)	220/380, 230/400	) 0.85Un-1.1Un	
Grid Connection Form	3L+N	I+PE	
Rated Input/Output Grid Frequency/Range	50Hz/45Hz-55Hz	60Hz/55Hz-65Hz	
Power Factor Adjustment Range	-1^	-1~1	
Total Current Harmonic Distortion THDi	<3% (of nom	<3% (of nominal power)	
DC Injection Current	<0.50	<0.5% In	
Efficiency			
Max. Efficiency	98.5	5%	
Euro Efficiency	97.8	3%	
MPPT Efficiency	>99	9%	
PCS Model	SUN-MPPT-	L01-EU-AM8	
PV String Input Data			
Max. PV Input Power (kW)	20	00	
Max. PV Input Voltage (V)	100	00	
Start-up Voltage (V)	20	00	
MPPT Voltage Range (V)	180-	180-850	
Full Load MPPT Voltage Range(V)	450-	450-850	
Rated PV Input Voltage (V)	60	600	
Max. Operating PV Input Current (A)	40+40+40+40+	40+40+40+40+40+40+40	
Max. Input Short-Circuit Current (A)	60+60+60+60+	-60+60+60	
No. of MPP Trackers	8	}	
Efficiency			
Max. Efficiency	>99	9%	
MPPT Efficiency	>99.	9%	

STS Module	SUN-STS500L			
Grid Side Data				
Rated AC Input/Output Active Power (kW)	500			
Rated AC Input/Output Current (A)		725		
Rated Input/Output Voltage(V)	22	0/380, 230/400 (three pha	se)	
Grid Connection Form		3L/N/PE		
Rated Input/Output Grid Frequency		50Hz/60Hz		
Load Side Data				
Rated Output Active Power (kW)		500		
Rated Output Current (A)		725		
Rated Output Voltage(V)	22	0/380, 230/400 (three pha	se)	
Grid Connection Form		3L/N/PE		
Rated Output Grid Frequency		50Hz/60Hz		
GEN Side Data				
Rated AC Input Active Power (kW)		500		
Rated AC Input Current (A)		725		
Rated Input Voltage(V)	22	0/380, 230/400 (three pha	se)	
Grid Connection Form		3L/N/PE		
Rated Input Grid Frequency		50Hz/60Hz		
Equipment Protection				
Integrated	DC Polarity Reverse Connection Protection, AC Output Overcurrent Protection, Thermal Protection, AC Output Overvoltage Protection, AC Output Short Circuit Protection, DC Component Monitoring, Overvoltage Load Drop Protection, Ground Fault Current Monitoring, Arc Fault Circuit Interrupter (optional), Power Network Monitoring, Island Protection Monitoring, Earth Fault Detection, DC Input Switch, Surge protection level			
Surge Protection Level	TYPE II(DC), TYPE II(AC)			
Interface				
LCD/LED display	LCD			
Communication Interface	WIFI, RS485, CAN, Meter			
General Data				
Off grid switching time		<30ms		
Operating Temperature Range(°C)	-2	5°Cto +60°C,>45°C Deratir	g	
Permissible Ambient Humidity		0-95%		
Permissible Altitude		4000m		
Ingress Protection(IP) Rating	IP 65(MPPT Module) IP 65(PCS Module) IP 20(STS Module		IP 20(STS Module)	
Cabinet Size(W×H×D)[mm]	543×197.8×700(MPPT Module)	543×310×775(PCS Module)	543×575×866(STS Module)	
Inverter Topology		Non-Isolated		
Over Voltage Category	OVC II(DC), OVC III(AC)			
Type of Cooling	Intelligent Air Cooling			
Warranty	5 Years/10 Years the Warranty Period Depends the Final Installation Site of Inverter, More Info Please Refer to Warranty Policy			
		IEC 61727, IEC 62116, CEI 0-21, EN 50549, NRS 097, RD 140, UNE 217002, OVE-Richtlinie R25, G99, VDE-AR-N 4105		
Grid Regulation	IEC 61727, IEC 62116, C			



#### Model

BOS-A

Main Parameters				
Cell Chemistry			LiFePO <sub>4</sub>	
Module Energy ( kWh )			7.68	
Module Nominal Voltage (V)			38.4	
Module Capacity (Ah)			200	
Module Dimension ( $W \times D \times H, mm$ )			601.5 × 520 × 135	
Module Weight Approximate ( kg )			70	
Battery Module Qty In Series ( Optional )		7	13	21
System Nominal Voltage ( V )		268.8	499.2	806.4
System Operating Voltage ( V )		235.2 ~ 306.6	436.8 ~ 569.4	705.6 ~ 919.8
System Energy ( kWh )		53.76	99.84	161.28
System Usable Energy ( kWh ) 1		48.38	89.85	145.15
Charge / Discharge <sup>2</sup>	Recommend	100		
Current ( A )	Max	160		
Working Temperature ( °C )		Charge : 0 ~ 55 / Discharge : -20 ~ 55		
Status Indicator		Yellow : Battery High Voltage Power On Red : Battery System Alarm		
Communication Port		CAN2.0		
Humidity		5% ~ 85%RH		
Altitude		≤3000m		
IP Rating of Enclosure		IP20		
Dimension ( W × D × H, mm )		610 × 610 × 1900	610 × 610 × 2350	(610 × 610 × 1900) × 2
Weight Approximate ( kg )		558	985	1586
Installation Location		Rack-Mounted		
Storage Temperature ( °C )		0 ~ 35		
Recommend Depth of Discharge		90%		
Cycle Life		≥6000 ( 25±2°C, 0.5C / 0.5C, EOL70% )		
Warranty <sup>3</sup>		10 years		
Certification		CE / IEC	62619 / IEC 62040 / UN38.3 /	/DE-2510

1. DC Usable Energy, test conditions : 90%DOD, 0.3C charge & discharge at 25°C. System usable energy may vary due to system configuration parameters.

2. The current is affected by temperature and SOC.

3. The warranty is due whichever reached first of warranty period or life cycle power.

#### Model



SUN-50K-SG01HP3-EU-BM4

© Battery Port: Dual independent battery circuit port, supporting multiple brand battery connetion and battery voltage range 160-800V. © Communication Port: Serve as communicate with battery and data exchange between inverter and extra devices.

© Load Port: Offer AC power to connected loads.

© Grid Port: Connect to utility grid, for bidirectional power transfer: importing from and exporting to the grid.

◎ Generator Port: Connect to diesel generator for backup power supply during outages, also can connect with existing solar inverter for AC Coupling.

◎ PV Input: Connect to PV panels with 4 MPPTs.

#### Model

#### SUN-80K-SG02HP3-EU-EM6



GEN

GRID



Load Port

- © Battery Port: Dual independent battery circuit port, supporting multiple brand battery connetion and battery voltage range 160-1000V. © Communication Port: Serve as communicate with battery and data exchange between inverter and extra devices.
- © Load Port: Offer AC power to connected loads.

◎ Grid Port: Connect to utility grid, for bidirectional power transfer: importing from and exporting to the grid.

 $\odot$  Generator Port: Connect to diesel generator for backup power supply during outages, also can connect with existing solar inverter for AC Coupling.

 $\odot\,$  PV Input: Connect to PV panels with 6 MPPTs.

#### **STS Module**

Smoothly switch between on-grid, off-grid, and diesel generator modes with a switching time of less than 10ms. Each diesel, load, and grid connection is independent, with each path supporting 500kW.



Model	BOS-A-PDU-2
Operating Voltage	200~1000Vdc
Max.Charge/Discharge Current	160A
Operating Temperature	-20~65°C
Ingress Protection	IP20
DC Input Rating	12±2%V/4.15A
Details	632×572×142.2(W×H×D),21kg



 $<sup>\</sup>odot$  Ethernet:Features not yet developed.

- © PCS COM:PCS COM battery communication terminal: used to output battery information to the inverter.
- $\odot$  IN COM:Connection position with previous BOS-A-PDU-4 communication input.
- $\odot$  OUT COM:Connection position with next BOS-A-PDU-4 communication output.

 $\ensuremath{\textcircled{\sc 0}}$  Isolating Switch: It is used to manually control the connection between the battery rack and external devices.

◎ USB:BMS upgrade port and storage expansion port.

© COMM1:Connection position of external 12VDC power supply.

- © COMM2:Used for communication and providing power.
- Iluetooth:The mobile APP connects to the data acquisition rod of the energy storage system.
- © B+:Battery common positive connection position (red).
- © B-:Battery common negative connection position (black).
- ◎ Display screen:Display SOC and fault codes.
- $\odot$  START: A start switch of 12VDC power inside the high-voltage control box.
- ◎ HV light indicator:High-voltage hazard indicator (yellow).
- $\odot\,$  ALRM light indicator:Battery system fault alarm indicator (red).
- $\odot$  PCS1+:First PCS positive connection position (orange).
- $\odot\,$  PCS2+:Second PCS positive terminal connection position (orange).
- $\odot\,$  PCS1-:First PCS negative connection position (black).
- $\odot\,$  PCS2-:Second PCS negative connection position (black).

#### Model

#### BOS-A-Pack7.68

Nominal Capacity	200Ah	Ingress Pr
Nominal Energy	7.68kWh	Operating
Nominal Voltage	38.4Vdc	Operating
Nominal Charge/Discharge Current	160A	Storage Te
Details	632×576×135.2(W×H×D),66kg	

Ingress Protection	IP20
Operating Temperature(Charge)	0~55°C
Operating Temperature(Discharge)	-20~55°C
Storage Temperature	0~35°C



 $\odot$  B-:Battery module negative pole (black).

- ◎ B+:Battery module positive pole (orange).
- © COMM1:Used for communication and providing power.
- © COMM2:Used for communication and providing power.

#### Model

BOS-A

#### BOS-A-Rack9 \*2

Can install 16 pcs batteries and 1 pcs High Voltage Battery cluster control box.

Dimension (  $W \times D \times H$ ) Weight Approximate 1220 × 610 × 1600mm 84kg



#### BOS-A-Rack11 BOS-A-Rack11 \*2

Can install 10 pcs batteries and 1 pcs High Voltage Battery cluster control box. Can install 21 pcs batteries and 1 pcs High Voltage Battery cluster control box.

Dimension (  $W \times D \times H$ ) Weight Approximate 610 × 610 × 1900mm 47kg



1220 × 610 × 1900mm 94kg



#### BOS-A-Rack14

Can install 13 pcs batteries and 1 pcs High Voltage Battery cluster control box.

Dimension (  $W \times D \times H$ ) Weight Approximate 610 × 610 × 2350mm 55kg



Backup Power Duration Plan	1 hours	2 hours	4 hours
Hybrid inverter power	100kW	50kW 80kW	50kW 80kW
Battery model	BOS-A160	BOS-A100 BOS-A160	BOS-A100 BOS-A160
Number of batteries	1 pc	1 рс 1 рс	2 pcs 2 pcs







50kW / 100kWh



**Typical Application Scenarios** 



Maximum support for 16 racks of batteries in parallel



Maximum support for 10 inverters in AC parallel operation



Maximum support for 16 clusters of batteries in parallel





## Deye Cloud All-in-one Energy & Device Management Platform

**Unlock Significant Savings** \$ 4. Individual Add-On for Dynamic Tariff 俞 Intelligent Charging/Discharging Strategies + **Tailored Solution to Deve Devices** Å **Real-time Equipment Monitoring** 1-12-07 \$450.00 Scan Device: 0 0.22 D 17 Dil Micro-Inv erter Local Mode Scanning nearby devices DY-3209203 AP-3209203 ×17.0 AP-3209203 AP-3209203 AP-3209203 AP-32 \$245.00 12024-12-07 Ē ß Η 0



# Smarten Up Your Home Energy

Download Deye Cloud APP to join us!

Embrace a seamless, effortless energy experience that's both ecofriendly and budget-friendly with our intelligent assistant

5

Deye ESS / Deye New Energy



in

(###)